

5.2. Warden Coil Boards

| Warden Coil Board | | | | | | | | |
|-------------------|----------------------------------|---------|-------------|-------|---------|--------------|-------|---------|
| Red Chain | | | Green Chain | | | Blue Chain | | |
| Wire | Coil | MOSFET# | Wire | Coil# | MOSFET# | Wire | Coil | MOSFET# |
| Red | Power | | Green | Power | | Blue | Power | |
| Red | Power | | Green | Power | | Blue | Power | |
| 0 Purple | Left Sling | Q8 | 8 Brown | Empty | Q9 | 16 Brown | Empty | Q10 |
| 1 White | Left Lower Flipper High | Q29 | 9 Orange | Empty | Q30 | 17 Orange | Empty | Q31 |
| 2 Black | Left Lower Flipper Low | Q11 | 10 Black | Empty | Q12 | 18 Black | Empty | Q13 |
| 3 Yellow | Magnet | Q26 | 11 Yellow | Empty | Q27 | 19 Yellow | Empty | Q28 |
| 4 Brown | Beetle Juice kicker | Q14 | 12 Purple | Empty | Q15 | 20 Purple | Empty | Q16 |
| 5 Orange | NONE | Q23 | 13 White | Empty | Q24 | 21 White | Empty | Q25 |
| 6 Pink | Knocker | Q17 | 14 Pink | Empty | Q18 | 22 Pink | Empty | Q19 |
| 7 Grey | Shaker | Q20 | 15 Grey | Empty | Q21 | 23 Grey | Empty | Q22 |

| Coil Expander Board | | | | | | | |
|---------------------|---------------------------|-----------------------------|---------|-------|-----------------------------|------------------------------|---------|
| Coil # | Green Chain – Top Plug | | MOSFET# | Coil# | Blue Chain – Bottom Plug | | MOSFET# |
| | Green | Power | | | Blue | Power | |
| | Green | Power | | | Blue | Power | |
| 55 | Purple | Lower Right Flipper high | B1 | 63 | Purple | Upper Flipper High | A1 |
| 54 | White | Auto Launch | B2 | 62 | White | Right Up Post | A2 |
| 53 | Black | Lower Right Flipper Hold | B3 | 61 | Black | Upper Right Flipper Hold | A3 |
| 52 | Yellow | Right Scoop | B4 | 60 | Yellow | Beetle Juice Pop (right) | A4 |
| 51 | Brown | Trough Eject | B5 | 59 | Brown | Lost Souls Scoop | A5 |
| 50 | Orange | Right Sling | B6 | 58 | Orange | Juno Scoop | A6 |
| 49 | Pink | Drop Reset | B7 | 57 | Pink | Mrs. Argentina Pop (left) | A7 |
| 48 | Grey | Drop Knockdown | B8 | 56 | Grey | Juno Pop (bottom) | A8 |